


WR2000A WELLER HOT AIR STATION (200W) | T0053378699N



SKU: T0053378699



WELLER WR 2000A REWORK STATION

WR 2000A - Digital hot air station, 200 W (300 W), equipped with internal pump.

Control unit features **2 independent channels** with automatic tool recognition function.

All tools with power up to 200 W are connectable (compatible series only).

Allows **simultaneous operation of 2 soldering tools** (ATTENTION: option NOT valid for hot air and desoldering irons; these tools are NOT compatible with simultaneous use).

Indications for simultaneous operations: the sum of the power of the 2 soldering irons must not exceed 255 W, and the maximum power of each iron must not exceed 120 W.

Weller product no.: **T0053378699N**.

Scope of delivery:

- **WR 2** (T0053377699N) – Two-channel digital control unit for soldering and desoldering, 250 W (300 W) / 230 V
- **HAP 1** (T0052711599N) - **Hot air iron 100 W** / 24 V provided with **R06** round nozzle for HAP 1 and HAP 200 (Ø 3.0 mm)
- **R04** (T0058727821) - Round nozzle for HAP 1 and HAP 200 (Ø 1.2 mm)
- **WDH 30** (T0051515299N) - Safety rest with dry cleaner for FE 75, LR 21 and TCPS irons.

Specifications

- Channels: 2
- Power: **200 W (300 W)**
- Supply voltage: 230 V
- Temperature range (depends on tool): **50 - 550 °C**
- Temperature accuracy: ± 9 °C
- Temperature stability: ± 2 °C
- **Built-in pump:** Periodic duty 30/30 s
- Capacity: **18 l/min**
- Max. vacuum: 0.7 bar
- Max. air flow rate (depends on tool): **10 l/min**
- Overcurrent release: 1.6 A
- Display: LCD
- ESD safe: Yes
- USB interface: No
- WT compatible: Yes
- IPC compliance: (Tip to ground) corresponds to IPC-J-001.